

SPS5000X Firmware Upgrade Instructions

Upgrade from a U-disk (USB Memory device)

WARNING: DO NOT shut off the instrument until the update is completed.

1. Copy the update file (*.ads) to a FLASH type U-disk, and then insert the U-disk into the host on the front panel.
2. Press the **Menu** button on the front panel, then use the **knob** and press it to get into the upgrading interface. "System" -> "Upgrade"




Figure 1





Figure 2

3. Use the **knob** to select the correct firmware version, then press the **knob** and will start to upgrade.



Figure 3

4. The upgrading is start, it will pop up the progress bar and will spend 3-5 minutes. When finish the upgrading, it will reboot by itself.
5. After the instrument reboots, check the version number through the **Menu** -> **System** -> **Version** to confirm if the upgrade is successful.



```
Model: SPS5042X
SPEC: 40U60A720W
SN: SPS42AAD4R0021
Ver.M : 3.1.1.6
Ver.S1: 00-00-006-000
```

WARNING: DO NOT shut off the instrument until the update is completed.